

February 4th, 2018

SP80 V3.35 Firmware Release

Introduction

This document is the firmware release notes of the [SP80 V3.35](#).

This version is a minor release with new features, improvements and bug fixing.

Upgrade Procedure

The customer can upgrade the receiver with version [V3.35](#) by following this procedure:

- 1- Copy the file [sp80_upgrade_v3.35.tar](#) to a SD Card (its size must be at least 256Mbytes, and it is preferable to use an empty and recently formatted SD Card)
- 2- Switch off the SP80
- 3- Plug the SP80 into an external power and make sure that there is also an internal battery
- 4- Insert SD Card to the SP80
- 5- Turn on the SP80 while keeping pressed the button 'Scroll' (during about 5 seconds)
- 6- Wait for the complete upgrade (it should take about 10 minutes)

Note that receiver has to be under warranty period to be upgraded.

Firmware list and versions

General version number: [V3.35 – 2/4/2018](#)

OS: [2.6.37 #800](#)

U-Boot: [1.32](#)

PVT: [LP73V19](#)

DSP: [LC73V19](#)

SL: [LS73V21](#)

WEB Service: [LW73V05](#)

HTML Pages: [LH73V10](#)

BT: [7.2.31](#)

PMU: [3.W](#)

GSM: [02.003](#)

XDL: [V01.14\(2\)](#)

The software compatible with SP80 [V3.35](#) are:

- FAST Survey: [5.0.3](#)
- Survey Pro: [6.2](#)
- Trimble Access: [2017.00](#)
- RINEX Converter: [4.7.1](#)

This document is for informational purposes only and is not a legally binding agreement or offer. Spectra Precision makes no warranties and assumes no obligations or liabilities hereunder.

© 2018, Trimble Inc. All rights reserved. Spectra Precision and the Spectra Precision logo are trademarks of Trimble Inc. its subsidiaries. All other trademarks are the property of their respective owners.

- Survey Office (64-bits): 4.0
- USB Serial Emulation: 1.1
- Spectra Precision Loader: 7.1.0
- Spectra Precision File Manager: 1.4.0

New Features (since the version 3.33)

No new features

Improvements (since the version 3.33)

1. **QZSS:** QZSS functionality updated to match the latest QZSS SiS ICD. It is possible to track signals from up to 4 QZSS SV. L1-SAIF signal is not considered SBAS-like anymore, so not tracked as master. L1s signal is being tracked as slave instead, and its data stream is output in DAT,FRM

Resolved Problems (since the version 3.33)

1. **ZDA:** The message NMEA ZDA returned the year 2017 instead of 2018. This problem is resolved.
2. **DCOL:** The command 53h CHANCTRL was rejected if the receiver did not contain the option GLONASS, GALILEO or BEIDOU. This problem is now resolved.
3. **BEIDOU:** Unhealthy Beidou satellites may reboot the receiver. This problem is now resolved.

Known issues

1. **Firmware Upgrade:** It is not recommended to upgrade the firmware with SP Loader using the serial cable. You must use the SD Card or the USB cable.
2. **Trimble Access:** To power up the SP80 modem, you will need to try the Internet setup wizard twice. The first attempts will probably time out.

Recommendations

1. **Beta version:** The official version contains 2 numbers (ex: 1.2). If the receiver contains a version with 3 digits (ex: 1.2.5), it means that it is a beta release and this beta release can be used only 90 days after the release date. After 90 days, the receiver will not answer to any command, and the only thing to do is to upgrade the receiver with an official version.
2. **SD Card:** The receiver supports the standard SD Card and the SDHC card up to 32Gb. It does not support the SDXC.
3. **Ionosphere activity:** Today we are at the peak of ionosphere activity which can affect/degrade receiver performance. User must realize that often 3rd party reference data provider is equally responsible for performance degradation because of generating much less correcting data compared to quiet ionosphere conditions. User is recommended also contacting Network data provider in case of RTK problems.
4. **ATL log:** We recommend end user in case of receiver performance problem to record atl.log and share it with Tech Support. W/o atl.log file, the ability to help end user will be much less.
5. **6 GNSS:** While SP80 can work with different subsets of GNSS (e.g. GLO only, BDS only, GLO+BDS), user must realize that exclusion of any available GNSS system may result in degraded positioning performance
6. **6 GNSS:** While SP80 can track, and use the observables from all 6 GNSS, for differential (RTK rover) operation it can be possible only if base provides respective reference data. Today with RTCM-3.1 protocols these reference data can be available only for L1/L2 GPS and GLONASS, so SP80 cannot take a benefit of other signals. Only the following 2 cases can allow effective RTK usage of all tracking signals:
 - Using own SP80 base generating either ATOM or RTCM-3.2 (MSM) differential data
 - Using 3rd party services supporting RTCM-3.2 (MSM) data generation
7. **NTRIP:** When working with Ntrip service, user is recommended to select VRS mount point over MAC and FKP. In general, with wide variety of different mount points, always try select points with multiple GNSS data.
8. **RINEX:** When converting receiver raw data to RINEX it is desirable to generate RINEX-3.2 (latest released version) data as legacy RINEX-2.11 does not support many of GNSS signals SP80 tracks.